

CARMENTA



CARMENTA
Watch X8 Ultra

Kullanma Kılavuzu

Türkçe versiyon



Uygulamayı indirmek ve kurmak için QR kodu tarayın.



HarmonyOS



Ürün ismi

Ana kontrol çipi

Radyo frekansı

Bluetooth versiyonu

Kalp sensörü

Enerji yönetimi

Ürün boyutu

Gövde malzemesi

Akıllı saat

XC2806

2.4 G BLE

5.0

Epco Micro EM7128


Polymer 3.7 V

45x38x11mm

Paslanmaz çelik +IML+
temperli cam


Ürünü Tanıyalım

1. Açma/kapatma için sağ tarafta bulunan tuşa 3 saniye boyunca basın.
2. Ürünün temel yapısını aşağıda gösterildiği şekilde anlayabilirsiniz.



Şarj

1. Şarj başlığının pinlerini saatin üzerindeki bağlantı noktasına yerleştirin (aşağıdaki resimde gösterildiği gibi) ve sonra şarj cihazının USB bağlantısını 5V/1A değerlerinde kaliteli bir adaptöre takın.
2. Bazı şarj cihazlarında manyetik çekim, otomatik hizalama veya yapısal hizalama bulunur. Şarj kablusunun ve saatin şarj girişinde mıknatıslar bulunmaktadır. Doğru hizalama yaparak takmaya dikkat edin.
3. Saatin şarjı sıfıra yakın iken, tam olarak şarj olması 2 saattir. Ürün kutusundan ilk çıkarıldığında şarjı bitik olarak gelebilir. Ürün açılmıyorsa şarja takın ve 2 saat boyunca şarj edin. Şarj edildiği halde hala açılmıyorsa bizimle irtibat kurun.





Ekranı uyandırmak için kısa basın;
Ekran açıldıktan sonra arayüze girdikten sonra
arayüzde seçim yapmak için döner
tuşu kullanılabilir veya elle seçim yapılabilir.

Dokunmatik Ekran Çalışması



Kısayol Menüsü



Su Geçirmezlik

Ürün su sıçramalarına karşı dayanıklıdır fakat tamamen su geçirmez değildir. Saat kolunuzda takılı iken; denize, havuza ve duşa girmeniz tavsiye edilmez. Ürünün doğrudan su ile teması halinde garanti dışı kalmaktadır. Saatin su haricinde; sabun, deterjan, şampuan, krem, losyon, alkol, temizleyici ve aşındırıcı kimyasallar vb. ile temas etmesi halinde su geçirmezliği bozulabilir. Bu gibi kimyasallar ile temas eden cihazlar garanti dışı kalmaktadır.

Temel Kullanım

- 1.Saat açıldıktan sonra 10 saniye herhangi bir işlem yapılmazsa, ekran otomatik olarak kapanacak ve uyku moduna geçecektir. (Ekran zaman aşımı süresi "ayarlar-parlaklık-ekran kapanma süresi" kısmından düzenlenebilir.) Saatin ekranını açmak için istediğiniz herhangi bir tuşa basabilirsiniz.
- 2.Saatte çoklu ekran arayüzü bulunmaktadır. Ekran arayüzünü değiştirmek için ana ekrana uzun tıklayın, sağa ve sola kaydırarak veya yan tuşu döndürerek diğer arayüze geçebilirsiniz. Mevcut arayüzleri kullanabilirsiniz veya saatin uygulaması içerisinde istediğiniz arayüzü seçerek indirebilirsiniz.
- 3.Ana ekranda, kayan ekran bölümündeki küçük ay resmini aktif hale getirerek "rahatsız etmeyin" modunu açık hale getirebilirsiniz.
- 4.Ana ekranda, ekranı aşağı kaydırarak "kısayol menüsü" ne girebilir ve tekrar yukarı kaydırarak kısayol menüsünden çıkabilirsiniz.
- 5.Ana ekranda, ekranı sağa kaydırmak, yaygın olarak kullanılan fonksiyon çubuğunu açar.(En son kullanılan özelliğe hızlıca girilebilir)

Hatırlatma: Saat üzerinde "telefon müziği", "saat müziği" veya "kulaklık" arasında geçiş yaparken, telefonunuz saatin bluetooth müzik özelliğinden otomatik olarak devre dışı kalacaktır. Eğer 5 dakika içerisinde tekrardan bluetooth müzik özelliğine geçiş yaparsanız, telefonunuz otomatik olarak yeniden bağlanacaktır. (Aksi durumda akıllı saat 5 dakika içerisinde bluetooth müzik özelliğini otomatik olarak devre dışı bırakır)

Kablosuz Kulaklık İle Saat Bağlantısı

Bu saat kablosuz kulaklıklarla bağlantı özelliğini destekler. Bağlantı arayüzüne girmek için resim 2'deki simgeye tıklayınız.

1. Eğer saat kulaklığınıza bağlanır ise, telefon ile olan bluetooth müzik bağlantısı otomatik olarak kesilecektir.
2. Kulaklık ile sadece saatte bulunan şarkıları dinleyebilirsiniz.



Resim 1



Resim 2

Ses Kayıt Fonksiyonu

Saatin kayıt fonksiyonu bulunmaktadır ve sağ tuşa 3 saniye basılı tutularak kaydı hızlı bir şekilde başlatabilirsiniz. Kaydı başlatmak/durdurmak için düğmeye 3 saniye uzun basın. Dosyalar saatin hafızasında saklanır. Kayıt arayüzünde (resim 3), kayıtları dinlemek için sola kaydırın (resim 4), ve ardından kayıt listesine gitmek için sola kaydırın (resim 5) ve oynat'ı seçin.



Resim 3



Resim 4



Resim 5

NFC Özelliđi

NFC kablosuz fonksiyonu ile, temel olarak erişim kontrolü için kullanılır

(oda, asansör, otopark girişı, kaydırma kartları vb.).

İlgili işlevler, cep telefonunuzun nfc'yi ve ilgili işlevsel uygulamaları desteklemesi gereklidir.

1.Erişim kartı özelliđi

Bu saat, sıradan erişim kartları veya erişim anahtarlarının yerini alabilecek bir NFC etiketine eşdeğerdur.

2. NFC kısayolları veya diđer uygulamalar

Cep telefonunuzdaki diđer NFC özellikli uygulamaları kullanmak için de kullanabilirsiniz (Apple cep telefonları için kısayol komutları gibi, ayrıntılar için lütfen cep telefonunun NFC ile ilgili talimatlarına ve uygulamalarına bakın).

Tuş talimatı

Ekranı açmak için kısa süreli basın. Ana menüye girmek için yan tuşa basın, geri dönmek için tekrar basın. Kısayol menüsü arayüzünde menü stillerini deđiştirmek için tıklayın. Kadran yakınlaşturma ve fonksiyonları deđiştirmek için yan tuşu çevirin. Genel çalışma ekranında geri dönmek için yan düğmeye basın.

Açma tuşu: Cihazı çalıştırmak için yan tuşa uzun basın. Ekranı açmak için kısa basın.

Dokunmatik ekran çalışması

kısayol menüsü-aşağı kaydır
kenar çubuđu-sađa kaydır
fonksiyon menüsü- sola kaydır
Bildirim-yukarı kaydır

Kısayol menüsü

Telefon bađlantı durumu
Ses Bluetooth deđiřimi
řİfre
DND modu
Batarya
Menü tipi deđiřimi
Parlaklık ayarı
Flaş ışığı

Hatırlatıcı: Saatin sesli görüşme fonksiyonu, ürün açıldığında otomatik olarak aktif hale gelmektedir. 2 dakika boyunca cep telefonunuzun bluetooth'u ile eşleştirilmezse, saatin sesli görüşme özelliği otomatik olarak kapatılacaktır.

Telefon İle Eşleştirme

1)Minumum IOS 9.0 ve Android 5.0 ile desteklenen akıllı telefonlar, bu akıllı saatin uygulaması yoluyla akıllı saatle eşleştirilebilir.

2)Uygulama kurulumu: Aşağıdaki Qr kodu okutun ve çıkan uygulamayı telefonunuza indirip kurulumu gerçekleştirin. Uygulama kurulumu veya kullanımı sırasında lütfen tüm izinleri istemlere göre etkinleştirin, aksi takdirde uygulamanın ve saatin normal kullanımını etkileyebilir.

3) Uygulama manuel kurulumu : QR kodu okutarak kurulum yapmak istemezseniz manuel olarak da kurulum sağlayabilirsiniz. “V Band” uygulamasını telefonunuzun uygulama marketinden indirin. “My watch” kısmına girin. “Cihaz ekle” seçeneğine dokunun. Telefonunuz bluetooth araması yaptıktan sonra Carmenta akıllı saatinizi seçerek bağlantıyı kurabilirsiniz.

Bağlanma başarılı olsa da olmasa da durumu menüde görebilirsiniz.

Sesli Görüşme Bağlantısı

Saatiniz kadrان ekranındayken ekranı yukarıdan aşağı doğru kaydırın. Saatin üst menüsünde soldaki bluetooth sembolüne dokunarak aktif hale getirin. Daha sonra telefon ayarlarından bluetooth ayarlarına girin. Sonunda “Audio” yazan özellik ile ek bağlantı kurun.

Not 1 : Sesli görüşmelerinizi saatinizden yapmak için 2. Bluetooth bağlantısının yapılması gerekmektedir. Bu özelliği saatinizden açıp kapatabilirsiniz.

Not 2 : Telefonunuzda izlediğiniz ve dinlediğiniz medya seslerinin saatinizden çıkmasını istemiyorsanız; sesli görüşme bağlantısını kurduktan sonra yan taraftaki ok işareti dokununuz. Alt tarafta çıkan “medya sesi” fonksiyonunu kapatın. İstediğiniz zaman açmak için aynı yolu izleyin.

Rehber Senkronizasyonu : Akıllı saatinize telefon rehberinizi aktarabilirsiniz. Telefon uygulamasına girin. " My Watch " sekmesine dokunun. "Diğer ayarlar bölümünde, "Rehber defterini senkronize et. " kısmına girdikten sonra manuel olarak kişi seçebilir veya hepsini seç özelliği ile tüm rehberinizi saate aktarabilirsiniz.

İpucu: Kısayol menüsünde Bluetooth sesini kapatıp açabilirsiniz. Sadece Bluetooth bağlantısı varken telefon müziğinin çalmasının yanı sıra saat arama yapıp sonlandırabilir.

Özellikler ve Fonksiyonlar

Sesli Asistan

Genel sesli asistan ile arama yapmak için işlev menüsündeki "Ses" işlevini de açabilirsiniz (örneğin: Lütfen **** arayın)

Müzik Fonksiyonu

Şarj kablosunu saatinize takın ve şarj kablosunun diğer ucunu bilgisayarınıza bağlayarak müziklerinizi saate yükleyin. Müzik çaları açın ve 3 moddan birini kullanmak için simgeye tıklayın.

Saat: saatte şarkıları çal

Telefon: Akıllı saatiniz, telefonunuzda çalan şarkıları kontrol eder.

(öncelikle akıllı saatteki müzik çaları açın)

Kulaklık: Bu akıllı saat, bluetooth kulaklık bağlantısını destekler. Saatinizi bluetooth kulaklığınıza bağlayarak akıllı saatinizde yüklü olan müzikleri dinleyebilirsiniz.

Diğer Özellikler ve Sık Sorulan Sorular

Temel özellikler

MP3 müzik: Saatte dahili hafıza bulunmaktadır. Ayrıca bluetooth ses cihazları ve kulaklıklarınızla eşleştirebilir ve saatinizdeki müzikleri dinleyebilirsiniz.

Ses kaydetme: Ses kaydetmek için yan düğmesine basılı tutup kaydı başlatabilir/kapatabilirsiniz. Cihazın arayüzünden kayıtlara ulaşabilir, cihazı bilgisayara bağlayarak kayıtları alabilirsiniz.

Günlük aktivite: Akıllı saatiniz, aktivitelerinizi takip eder. Adım sayınızı, kalerinizi, katettiğiniz mesafeyi takip edebilirsiniz.

Sesli görüşme: Akıllı saat bluetooth bağlantısı kurarak sesli aramaları destekler. Telefonunuz ile ek bağlantı kurarak aramalarınızı saat üzerinden yapabilirsiniz.

Bildirim: Telefonunuza gelen tüm bildirim ve mesajları saatinizden görüntüleyebilirsiniz. Saatiniz kadrان ekranındayken ekranı yukarı kaydırduğınızda bildirim kısayoluna erişebilirsiniz.

Yerel saat yüzü: Saatin kadrانını değiştirmek için ekrana basılı tutun ve sağa/sola kaydırarak seçim yapın. Yan taraftaki tuşu döndürerek de kadrان değişimi yapabilirsiniz. Telefon uygulamasından istediğiniz kadranı indirebilir veya kendi kadrانınızı özelleştirebilirsiniz.

Özelleştirme : Telefon uygulamasından "Arama kütüphanesi" bölümüne girin. "Özel arka plan" kısmından istediğiniz görseli ekrana ayarlayın veya alt taraftaki hazır kadrانlardan birini seçerek saatinize yükleyin.

Her zaman açık ekran : Akıllı saatin Always on display özelliği bulunmaktadır. Kadrان ekranını aşağı doğru kaydırarak saatin arayüzünden ulaşabilirsiniz.

Spor modu: Akıllı saatiniz yapmış olduğunuz sporu takip eder ve analiz halinde size sunar. Yaptığı analizleri kendi hafızasında tutar, telefon uygulaması ile eşleştirildiğinde tuttuğu verileri senkronize eder.

Sağlık ekranı: Bu saat ve uygulama kullanıcıya kapsamlı ve sistematik sağlık ve güvenlik işlevleri sağlarlar. Ancak, bu saat profesyonel tıbbi cihaz değildir. İlgili test verileri sadece günlük referans içindir ve tıbbi teşhiste kullanılmaz.

Kalp atış sayacı: Saat bileğe doğru sıklıkta takılarak kullanıcının kalp atış hızını ölçer.

Kan basıncı testi: Saat bileğe doğru sıklıkla takılarak kullanıcının kan basıncını ölçer.

Kan oksijen testi: Saat bileğe doğru sıklıkla takılarak kullanıcının kan oksijen seviyesini ölçer.

Uyku ekranı: Saat bileğinizde takılıyken uykuya daldığınızda derin/hafif uyku saatinizi 21:00'den itibaren otomatik olarak algılar.

Su hatırlatıcısı: Su hatırlatmaları almak için bir su hatırlatıcısı kurun.

Hareketsizlik hatırlatması: Bir oturma uyarısı ayarlayın ve uzun süre hareketsiz kaldığınızda akıllı saatiniz size otomatik olarak hatırlatacaktır.

Nefes alıp verme eğitimi: Akıllı saatte gösterildiği gibi nefes alıp verin.

Otomatik ölçüm özelliği: Otomatik kalp atış zaman Ölçümünü -Uygulamalar- Saatim- Diğer ayarlar- kısmında açabilirsiniz

Yardımcı fonksiyon: Ulaşılabilirlik özellikleri ya da aygıtları saati daha iyi kullanmanıza olanak tanır. Akıllı saatin ve telefon uygulamasının çok daha fazla işlevi bulunmaktadır. Yapmanız gereken deneyimlemek ve uygulamaktır.

Bilek sensörü : Elinizi yüzünüze doğru kaldırın. Ekran otomatik olarak açılacaktır.

Hava durumu: Telefon uygulaması ile senkronize olarak saatinizden hava durumunu anlık ve güncel olarak görün.

Kronometre: Kronometre özelliği ile herhangi bir etkinliğinizin süresini tutun.

Alarm: "Özellikler-Alarm" bölümünden ayarlayın. Saat otomatik olarak sizi uyaracaktır.

Rahatsız Etmeyin Modu: Tüm arama ve bildirimleri tek tuşla sessize alın.

Uzaktan Deklanşör: Telefon uygulamasından "uzaktan kontrol selfie" özelliğini açın, ardından saat deklanşör simgesini ekranda gösterecektir. Uzaktan fotoğraflar çekmek için saat ekranına tıklayın.

Saati bul: Açmak için, "Telefon uygulaması-Diğer ayarlar-Saati bul", saati bulmak için uygulama üzerinden saati bul sekmesine tıkladığınızda saatiniz titreşim bildirimi verecektir.

Telefonu bul: Saat üzerinden "Özellikler menüsü-Telefonu bul", telefonu bulmak için saat üzerinden "telefonu bul" sekmesine tıkladığınızda telefonunuz titreşim ve zil sesi bildirimi verecektir.

Kilit ekranı: Kilit ekranı şifresini saat ayarlarından aktif hale getirebilirsiniz.

Mini oyun: Yerleşik 2 mini oyun (fun puzzle, tetris)

Güç tasarrufu: Güç tasarruf modunu aktif edin, saat sesi otomatik olarak kapatılacaktır.

Takvim: Saatiniz üzerinden takvime erişin.

El feneri: Aktifleştirildiğinde saat ekranını beyaz yaparak saatin el feneri işlevi yapmasını sağlar.

Kenar çubuğu: Açmak için saatin ana ekranında sağa kaydırın.

SOS: Tek tuşla acil yardım araması başlatın.

Yazılım Güncellemesi: Saat üzerinde en son yazılım güncellemesini görebilirsiniz ve eğer yeni güncelleme varsa son sürümüne güncelleme yapabilirsiniz.

Fabrika ayarları: Saat ayarlarından veya telefon uygulamasından "Saatim-Diğer ayarlar-Fabrika ayarları" seçerek saatinizi sıfırlayın.

S1: Akıllı saati kullanırken sürekli olarak telefona bağlı kalması gerekiyor mu?

1)Saatinizin sesli görüşme, bildirim ve uzaktan telefon kontrolü gibi özelliklerinin dışında kalan tüm özellikleri, telefon ile bağlantı kurmadan da kullanabilirsiniz. Adım sayma, uyku takibi, kalp ritmi, kan basıncı, kan oksijen değeri algılama, alarm, hatırlatmalar, ekranı açmak için elinizi kaldırın, rahatsız etmeyin, egzersiz modları gibi özellikler için bluetooth bağlantısı gerekmez. Akıllı saatiniz yaptığı ölçümleri hafızasına kayıt eder (belirli bir adete kadar) ve telefon uygulaması ile bağlantı kurduğunuzda otomatik olarak senkronize eder. Bununla birlikte, algılanan ve ölçülen verilerin uygulama üzerinden görüntülenmesi için uygulamaya senkronize edilmesi, kayıt ve istatistiksel analiz oluşturması için bluetooth bağlantısı gereklidir.

2)Çağrı bildirimleri, SMS bildirimleri, üçüncü taraf uygulama bildirimleri, uzaktan fotoğraf çekme gibi özellikleri kullanabilmek için bluetooth bağlantısı gereklidir.

3)Telefon çağrılarını açmak/reddetmek, telefon müzik kontrolü, gibi özellikleri kullanabilmek için bluetooth bağlantısı gereklidir.

S2: Telefon ile saat arasındaki bağlantı otomatik olarak kesildiğinde ne yapmalıyım ?

1)Saat ile telefon arasındaki bluetooth bağlantı mesafesi gerektiğinden uzak olduğunda bağlantı otomatik olarak kesilecektir. Telefon ile saatin bağlantı için yeterli mesafeye geldiğinde bağlantı otomatik olarak sağlanacaktır.

2)Eğer telefondan saat uygulaması kaldırılırsa veya uygulamalar penceresinden kapatılırsa, bluetooth bağlantısı kesilecektir. Lütfen telefon ayarlarında "Arka planda çalışma" özelliğini aktif hale getirin.

S3: Mesajın iletilmesi gecikirse ya da mesaj kaybolursa ne yapmalıyım?

Gecikmiş ve kaybolmuş mesajlar aşağıdaki nedenlerden dolayı olabilir:

1) Mesaj merkezi yaklaşık 15 mesajı tutar ve dairesel bir şekilde eski mesajları temizler bu yüzden saat sadece en son mesajları gösterir.

S4: Saatin kullanım süresini nasıl uzatabiliriz?

Batarya ömrü kullanım sıklığıyla ilgilidir. Aşağıdakiler gibi batarya süresini uzatabilirsiniz.

1) Kullanmadığınız fonksiyonları kapatın.

2) Saatin ve telefonun bluetooth bağlantısı sık sık kopuyorsa her bağlantı için ekstra güç tüketir. Telefonla işiniz yoksa, saat ve telefon arasındaki bluetooth bağlantısını kesebilirsiniz ve ve saati cep telefonundan Bluetooth'un etkin mesafesinden daha fazla ayırmamaya çalışarak kullanım süresini uzatabilirsiniz.

3) Saatin ekranı oldukça yüksek güç tüketir. Bu yüzden ekranın parlaklığını azaltmaya çalışın.

4) Her zaman açık ekran özelliğini sürekli aktif olarak kullanmak yüksek pil tüketimine sebep olabilir. Kullanmadığınız zamanlarda bu özelliği kapatarak pil tüketimini düşürebilirsiniz.

S5: Saat hatırlatmaları alabilir mi ?

Android Cihaz Ayarları:

1) Telefon uygulaması üzerinden mesajlar ayarının açık olduğundan emin olun.

2) Gelen mesajların normal olarak görüntülenip görüntülenmediğinden emin olun. Saat'in mesaj bildirimlerini alabilmesi için telefonunuza gelen mesajların telefonun bildirim merkezinde görüntülenmesi gerekir. Saat telefonunuza gelen bildirimleri anlık olarak alıp size gösterir.

Apple Cihaz Ayarları:

1) Aşağıdaki durumlarda eşleştirmeye izin vermeyi seçtiğinizi onaylayın. Telefon üzerinden "Ayarlar-Bluetooth" sekmesinden kontrol edebilirsiniz.

2) "Ayarlar-Bildirimler- SMS, Telefon Çağrıları" sekmesine gelerek bildirimlerin bildirim merkezinde görüntülenmesi ayarını aktif edin.

S7:Bluetooth bağlantısı başarısız olursa ne yapmalıyım? (Bağlantı-Yeniden bağlanma başarısız ya da bağlantı zayıf)

- 1)Bluetooth bağlantısındaki sinyal paraziti sorunundan dolayı her seferinde bağlanmak çok uzun sürebilir. Bağlantı uzun bir süre sağlanmazsa lütfen işlemin manyetik alan veya birden fazla Bluetooth cihazından kaynaklanan parazit olmayan bir ortamda gerçekleştirildiğinden emin olun.
- 2) Bluetooth'u kapatın ve yeniden açın.
- 3) Telefonunuzdaki arka plan uygulamalarını kapatın veya telefonunuzu yeniden başlatın.
- 4) Telefonunuzu diğer bluetooth aygıtları veya özellikleri ile aynı anda bağlamaya çalışmayın. Uygulama arka planda çalışmadığı sürece saat ile bağlantı kurulamaz.

Dikkat Edilmesi Gerekenler

- 1)Saatin bataryasının ömrünü uzun tutmak için; ilk şarjdan sonraki kullanımlarda saatin şarjının tamamen boşalmadan önce şarj etmeye ve uzun süre şarjda takılı halde bırakmamaya özen gösterin. Aksi takdirde pil sağlığı etkilenebilir.
- 2)Saatin şarj girişi ile şarj kablosunu bir bez yardımıyla düzenli olarak temizleyin. Saati ve kabloyu temizlemek için aşındırıcı kimyasallar kullanmayın.
- 3)Sizin ve çevrenizin sağlığı için kaliteli şarj adaptörü kullanmaya dikkat edin. 5V-1A değerlerindeki kaliteli şarj adaptörleri ile şarj edilmesi tavsiye edilir.
- 4)Ürün ıslak veya nemliyen şarj etmeyin. Saatiniz veya şarj kablosu zarar gördüyse kullanmayın. Bizimle irtibata geçin.
- 5)Şirketimiz; üründe ve kılavuzda, herhangi bir bildirimde bulunmaksızın değiştirme hakkını saklı tutar.

KUTU İÇERİĞİ

- 1) Carmenta Smart Watch
- 2) Şarj kablosu
- 3) Kullanma kılavuzu
- 4) Garanti belgesi

CARMENTA



CARMENTA

Watch X8 Ultra

User Manual

English Version



Download the app and
Scan the QR code to install.



HarmonyOS

Product name	Smart Watch
Main control chip	XC2806
Radio frequency	2.4 G BLE
Bluetooth version	5.0
Heart sensor	Epcu Micro EM7128
Energy management	Polymer 3.7 V
Product size	45x38x11mm
Materials	Stainless Steel +IML+ Tempered Glass


Understand Product

1. Press the button on the right for 3 seconds to turn on/off.
2. You can understand the basic structure of the product as shown below.



Charging

1. Put the pins of the charging head into the port on the watch (as shown in the picture below) and then plug the USB connector of the charger into a good quality 5V/1A adapter.
2. Some chargers have magnetic attraction, auto-align, or structural alignment. There are magnets in the charging port of the charging cable and the watch. Take care to install with correct alignment.
3. When the charge of the watch is close to zero, it takes 2 hours to fully charge. When the product is first taken out of the box, the battery may be dead. If the product does not turn on, plug it into the charger and charge it for 2 hours. If it still does not turn on after being charged, contact us.





Rotate Button

Short press to wake up the screen;
After you enter the interface after the screen is turned on, you can use the rotary key to make a selection in the interface or you can make a selection manually.

Open Key

Touch Screen Operation

Swipe Down

Shortcut Menu

Swipe Right
Sidebar



Swipe Left
Function Menu



Swipe Up

Notification Center

Shortcut Menu

App Connection State

Bluetooth Switch

Password

DND Mode



Battery Icon

Function Menu
Style Switch

Brightness
Adjustment

Screen Time

Waterproof Instructions

The product is splash resistant, but not completely waterproof.

While the watch is on your wrist; It is not recommended to swim. If the product comes into direct contact with water, it is out of warranty. Except for the water of the watch; soap, detergent, shampoo, cream, lotion, alcohol, cleaner and abrasive chemicals etc. If it comes into contact with water, it may deteriorate the waterproofing. Devices that come into contact with such chemicals are out of warranty.

Basic Use

1. If there is no operation for 10 seconds after the watch is turned on, the screen will automatically turn off and go into sleep mode. (Screen timeout period can be adjusted in "settings-brightness-screen-off time" section.) You can press any key you want to turn on the watch's screen.
2. The watch has a multi-screen interface. To change the screen interface, long click on the home screen, you can switch to the other interface by swiping right and left or rotating the side key. You can use existing interfaces or from within the watch app. You can download by selecting the interface you want.
3. On the main screen, you can activate the "do not disturb" mode by activating the small moon image in the floating screen section.
4. On the main screen, you can enter the "shortcut menu" by swiping down the screen and exit the shortcut menu by swiping up again.
5. On the home screen, swiping right opens the commonly used function bar. (The last used feature can be quickly entered)

Reminder: When switching between "phone music", "clock music" or "earphone" on the watch, your phone will be automatically disabled from the bluetooth music feature of the watch. If you switch to the bluetooth music feature again within 5 minutes, your phone will automatically reconnect. (Otherwise, the smart watch will automatically disable the bluetooth music feature within 5 minutes).

Connection with Wireless Headphones

This watch supports connectivity with wireless headphones. Click the icon in picture 2 to enter the connection interface.

1. If the watch is connected to your headset, the bluetooth music connection with the phone will be automatically disconnected.
2. You can only listen to the songs in the watch with the headphone.



Picture 1



Picture 2

Voice Recording Function

The watch has a recording function and you can start the recording quickly by pressing the right button for 3 seconds. Long press the button for 3 seconds to start/stop recording. The files are stored in the memory of the watch. In the recording interface (pic. 3), swipe left to listen to the recordings (pic. 4), then swipe left to go to the recording list (pic. 5) and select play.



Picture 3



Picture 4



Picture 5

NFC Feature

With NFC wireless function, it is mainly used for access control (room, elevator, parking lot entrance, swipe cards, etc.). Related functions, your mobile phone must support NFC and related functional applications.

1. Access card feature

This watch is equivalent to an NFC tag that can replace ordinary access cards or access keys.

2. NFC shortcuts or other apps

You can also use it to use other NFC-enabled applications on your mobile phone (such as shortcut commands for Apple mobile phones, please refer to the mobile phone's NFC-related instructions and applications for details).

Key instruction

Short press to turn on the screen. Press the side key to enter the main menu, press again to return. Click to change menu styles in the shortcut menu interface. Turn the side key to zoom the dial and switch functions. Press the side button to return to the general operating screen.

Open key: Long press the side button to start the device. Short press to turn on the screen.

Touch screen operation

shortcut menu-scroll down
sidebar-swipe right
function menu - swipe left
Notification-swipe up

Shortcut menu

Phone connection status
Audio Bluetooth exchange
Password
DND mode
Battery
Menu type change
brightness adjustment
Flash light

Reminder: The watch's voice call function is automatically activated when the product is turned on. If it is not paired with your mobile phone's bluetooth for 2 minutes, the watch's voice call feature will be turned off automatically.

Pairing with Phone

1) Smartphones supported with minimum IOS 9.0 and Android 5.0 can be paired with the smart watch through the app of this smart watch.

2) Application installation: Read the following Qr code and download the application to your phone and perform the installation. During app installation or use, please enable all permissions as prompted, otherwise it may affect normal use of app and watch.

3) Application manual installation: If you do not want to install by scanning the QR code, you can also install manually. Download the "V Band" application from your phone's application market. Enter the "My watch" section. Tap on 'Add device'. After your phone makes a bluetooth search, you can establish the connection by selecting your Carmenta smart watch.

You can see the status in the menu whether the connection was successful or not.

Voice Call Connection

While your watch is on the face screen, swipe down from the top of the screen. Activate it by touching the bluetooth symbol on the left in the top menu of the watch. Then go to bluetooth settings from phone settings. With the feature that says "Audio" at the end connect.

Note 1 : In order to make voice calls from your watch, a 2nd Bluetooth connection must be made. You can turn this feature on or off from your watch.

Note 2 : If you do not want the media sounds you watch and listen on your phone to come out of your watch; After establishing the voice call connection, tap the arrow on the side. Turn off the "media sound" function at the bottom. Follow the same path to open it whenever you want.

Contacts Synchronization: You can transfer your phone book to your smartwatch. Enter the phone app. Tap on the "My Watch" tab. In the "Other settings" section, select "Sync contacts book. After entering the "" section, you can manually select a contact or transfer all your contacts to the watch with the select all feature.

Tip: You can turn the Bluetooth sound off and on in the shortcut menu. In addition to playing phone music only when there is a Bluetooth connection, the watch can make and end calls.

Features and Functions

Voice Assistant

You can also open the "Voice" function in the function menu to search with the general voice assistant (for example: Please call ****)

Music Function

Plug the charging cable into your watch and connect the other end of the charging cable to your computer and upload your music to the watch. Open the music player and click the icon to use one of the 3 modes.

Watch: play songs on the watch

Phone: Your smartwatch controls the songs playing on your phone.

(first open the music player on the smartwatch)

Headphone: This smart watch supports bluetooth headphone connection. By connecting your watch to a bluetooth headset, you can listen to the music installed on your smart watch.

Other Features and FAQ

Basic Features

MP3 music: The watch has internal memory. You can also pair it with your bluetooth audio devices and headphones and listen to the music on your watch.

Voice record: To record audio, you can start/stop recording by pressing and holding the side button. You can access the records from the interface of the device, and get the records by connecting the device to the computer.

Daily activity: Your smartwatch tracks your activities. your step count, calories, You can track the distance you have traveled.

Voice call: The smart watch supports voice calls by establishing a bluetooth connection. By establishing an additional connection with your phone, you can make your calls through the watch.

Notification: You can view all notifications and messages coming to your phone from your watch. When your watch is on the face screen, swipe up to access the notification shortcut.

Clock face: To change the watch face, press and hold the screen and swipe left/right to make a selection. You can also change the dial by turning the button on the side. You can download the face you want from the phone app or customize your own face.

Customize: From the phone app, enter the "Search library" section. Set the image you want to the screen from the "Custom background" section or upload it to your watch by choosing one of the ready-made dials at the bottom.

Always on display: The smart watch has an Always on display feature. You can access the watch's interface by swiping down on the dial screen.

Sport mode: Your smart watch monitors the sport you have done and presents it to you in analysis. It keeps the analyzes it performs in its own memory, and synchronizes the data it keeps when paired with the phone application.

Health: This watch and app provide the user with comprehensive and systematic health and safety functions. However, this watch is not a professional medical device. The relevant test data is for daily reference only and is not used in medical diagnosis.

Heart rate counter: The watch is worn tightly on the wrist and measures the heart rate of the wearer.

Blood pressure: The watch is worn correctly on the wrist and measures the wearer's blood pressure.

Blood oxygen: The watch is worn tightly on the wrist and measures the wearer's blood oxygen level.

Sleep screen: When you fall asleep while wearing the watch on your wrist, it automatically detects your deep/light sleep time from 21:00.

Water reminder: Set up a water reminder to receive water reminders.

Inactivity reminder: Set a sitting alert and your smartwatch will automatically remind you when you've been inactive for a long time.

Breathing training: Inhale and exhale as shown on the smartwatch.

Otomatik ölçüm özelliği: You can turn on automatic heart rate measurement in - Applications-My watch-Other settings-

Auxiliary function: Accessibility features or devices allow you to make better use of the watch. The smart watch and the phone app have many more functions. All you have to do is experience and practice.

Wrist sensor: Raise your hand towards your face. The screen will turn on automatically.

Weather: See the weather forecast instantly and up-to-date from your watch in sync with the phone app.

Stopwatch: Keep time of any activity with the stopwatch feature.

Alarm: Set it in the "Properties-Alarm" section. The watch will automatically alert you.

DND mode: Mute all calls and notifications with one click.

Remote Shutter: Turn on "remote control selfie" from the phone app, then the watch will display the shutter icon on the screen. Click on the clock screen to take photos remotely.

Find watch: To turn it on, "Phone app-Other settings-Find time", click the find time tab on the app to find the time, and your watch will vibrate.

Find phone: When you click "Features menu-Find phone" on the watch, and "find phone" on the watch to find the phone, your phone will give a vibration and ringtone notification.

Lock screen: You can activate the lock screen password from the watch settings.

Mini game: 2 built-in mini-games (fun puzzle, tetris)

Power saving: Activate the power saving mode, the clock sound will be turned off automatically.

Calendar: Access the calendar on your watch.

Flashlight: When activated, it makes the watch display white, making it a flashlight.

Sidebar: Swipe right on the watch's home screen to open it.

SOS: Initiate a one-touch emergency call.

Software update: You can see the latest software update on the watch and if there is a new update, you can update to the latest version.

Fabrika reset: Reset your watch by selecting "My Watch-Other settings-Factory settings" from the watch settings or the phone app.

Q1: Does the smart watch need to be constantly connected to the phone while using it?

1) You can use all the features of your watch, such as voice calls, notifications and remote phone control, without connecting to the phone. No bluetooth connection is required for features such as step counting, sleep tracking, heart rhythm, blood pressure, blood oxygen value detection, alarm, reminders, raise your hand to turn on the screen, do not disturb, exercise modes. Your smart watch saves the measurements (up to a certain number) in its memory and automatically synchronizes it when you connect it with the phone application. However, a bluetooth connection is required for synchronizing the detected and measured data to the application for viewing via the application, creating recording and statistical analysis.

2) Bluetooth connection is required to use features such as call notifications, SMS notifications, third-party application notifications, remote photo taking.

3) Bluetooth connection is required to use features such as turning on/rejecting phone calls, controlling phone music, etc.

Q2: What should I do when the connection between the phone and the watch is automatically disconnected?

1) When the bluetooth connection distance between the watch and the phone is far from necessary, the connection will be disconnected automatically. When the phone and the watch are within sufficient distance for connection, the connection will be established automatically.

2) If the clock application is removed from the phone or closed from the applications window, the bluetooth connection will be disconnected. Please activate the "work in the background" feature in the phone settings.

Q3: What should I do if the delivery of the message is delayed or the message is lost?

- 1) Delayed and lost messages may be due to the following reasons.
- 2) The message center holds about 15 messages and clears old messages in a circular fashion so the watch only shows the most recent messages.

Q4: How can we extend the usage time of the watch?

Battery life is related to frequency of use. You can extend the battery life as follows.

- 1) Turn off the functions you are not using.
- 2) If the bluetooth connection of the watch and the phone is disconnected frequently, it consumes extra power for each connection. If you are not busy with the phone, you can disconnect the bluetooth between the watch and the phone, and try not to separate the watch from the cell phone more than the Bluetooth's effective range, thus prolonging its usage time.
- 3) The display of the watch consumes quite a lot of power. So try to reduce the brightness of the screen.
- 4) Actively using the always-on display feature may cause high battery consumption. You can reduce battery consumption by turning this feature off when you are not using it.

Q5: Can the watch receive reminders?

Android Device Settings:

- 1) Make sure the messages setting is turned on via the phone app.
- 2) Make sure that incoming messages are displayed normally.

In order for the Watch to receive message notifications, the messages received on your phone must be displayed in the notification center of the phone. The watch instantly receives notifications from your phone and shows them to you.

Apple Device Settings:

- 1) Confirm that you have chosen to allow pairing in the following cases. You can control it from the "Settings-Bluetooth" tab on the phone.
- 2) Go to the "Settings-Notifications-SMS, Phone Calls" tab and enable the notifications to be displayed in the notification center.

Q7: What should I do if the Bluetooth connection fails? (Connection-Reconnect failed or poor connection)

- 1) It may take a long time to connect each time due to the signal interference problem in the Bluetooth radio connection. If the connection is not established for a long time, please make sure that the operation is performed in an environment without interference from magnetic fields or multiple Bluetooth devices.
- 2) Turn Bluetooth off and then on again.
- 3) Close background apps on your phone or restart your phone.
- 4) Do not try to connect your phone with other bluetooth devices or features at the same time. The clock cannot be connected unless the application is running in the background.

Things to pay attention

- 1) To keep the battery life of the watch long; When using after the first charge, be careful to charge the watch before it is completely discharged and not leave it plugged in for a long time. Otherwise, battery health may be affected.
- 2) Regularly clean the charging port of the watch and the charging cable with a cloth. Do not use abrasive chemicals to clean the watch and cable.
- 3) Be careful to use a quality charging adapter for the health of you and your environment. It is recommended to charge with quality charging adapters of 5V-1A.
- 4) Do not charge when the product is wet or damp. Do not use if your watch or charging cable is damaged. Contact us.
- 5) Our company; reserves the right to change the product and the manual without notice.

BOX CONTENTS

- 1) Carmenta Smart Watch
- 2) Charging cable
- 3) User manual
- 4) Warranty certificate